

MONITOR VEO-XS WIFI 4,3" DUOX PLUS

**Referência:** 9449

VEO-XS WIFI está equipado com conexão Wi-Fi que permite o desvio de chamadas a dispositivos móveis. Graças à aplicação BLUE da Fermax, disponível de forma gratuita na Play Store e App Store, as funções...

DESCRIÇÃO

VEO-XS WIFI está equipado com conexão Wi-Fi que permite o desvio de chamadas a dispositivos móveis. Graças à aplicação BLUE da Fermax, disponível de forma gratuita na Play Store e App Store, as funções do videoporteiro podem ser geridas, directamente, desde um smartphone ou tablet, para te conectares a tua casa, onde quer que estejas. O monitor VEO-XS WIFI DUOX mãos livres caracteriza-se pelo seu reduzido tamanho e espessura, extra-plano. Graças ao seu menu OSD e disposição dos botões, a sua interação com o utilizador resulta de forma sensata e intuitiva. Fabricado em plástico ABS de alto impacto. Acabamento texturizado para limpeza fácil, e proteção ultravioleta para torná-lo mais resistente à luz solar. Inclui ecrã panorâmico a cores de 4,3" (16:9). O seu desenho equilibrado de linhas puras é distinto, moderno e minimalista.

ESPECIFICAÇÕES TÉCNICAS

GENERAL CHARACTERISTICS

Technology: DUOX PLUS (non-polarised 2 wire full digital system)
Audio/Video system: Audio/Video Color
Set-up (Installation): Surface mounted (order connector ref. 9447 separately)
Desktop support: Yes (ref. 9420)
Hands-free communication: Yes
Press-to-talk communication configurable: Yes
Induction loop: No (order monitor ref. 9459 with induction loop)
Screen dimensions: 4,3" (Panoramic 16:9)
Screen resolution (H x V): 480 x 272
Color of the product: Matt white
Number of pushbuttons: 5
Kind of pushbuttons: Mechanical (silicone)
Number of leds for lighted indications: 3 (red, blue, green with different states)

PROGRAMMING OF THE TERMINAL ADDRESS

From the terminal: From the OSD menu
From the outdoor panel or guard unit: Yes
From the outdoor panel throughout the apartment door bell: Yes

FEATURES

Automatic picture capture when the visitor calls (PHOTOCALLER): Yes (1 photo/call, until 150 photos, 368 x 288 pixels). This feature can be enabled by the user. Disabled by default.

Guard unit call: Yes (by means of the door release button)

Auto-on: Yes (with 3 outdoor panels/cameras)

OSD menu: Yes

Additional function F1: Yes (Button F1 sends a negative and/or command)

Additional function F2: Yes (it only sends command, no negative)

Apartment door bell differentiated from the outdoor panel: Yes

Connection for additional devices (call extension, light/buzzer activator, etc.): Yes (ref. 2040, ref. 2438, ref. 3267)

Additional terminals on the same address: Yes, max. 2 additional terminals (additional power supply can be required)

Doormatic (automatic door release for offices, etc.): Yes (configurable until 12h). Green Led ON.

ADJUSTMENTS

Date and time: Yes

Ring tones selection: Yes (5). Configurable for Block Panel 0, Block Panel 1, General Entrance Panel 0 and Concierge unit.

Call volume control: Yes (10 levels by OSD menu)

Do-not-disturb mode: Yes (by OSD menu) + Red led indication

Audio volume control: Yes (10 levels by OSD menu)

Brightness, color and contrast control: Yes (by OSD menu)

TECHNICAL FEATURES

Product dimensions (width x height x depth) mm: 125 x 165 x 21

Time to answer or open the door since the call is done: 30 s.

Conversation time: 90 s.

Conversation privacy: Yes

Voltage: 18-24 Vdc

Maximum consumption: 6.9 W

Standby consumption (paired and connected): 1.3 W

Working temperature (°C, °F), Humidity: [-5°C, +40°C][23°F, 104°F], [0%, 90%]

Line adaptor included in the terminal: Yes (A, C, default position OFF)

Connections: Bin, Bin, Bout, Bout, -, A+, F1, T

CALL FORWARDING (APP "BLUE" FOR SMARTPHONES & TABLETS)

Call forwarding to smartphones and tablets: Yes (App Compatible with iOS>=11, Android>=6)

Connectivity: Wifi (2,4 Ghz) and 3G/4G

Pairing of the monitor with the wifi router of the house: Once the App is installed, the user must register first. Pairing by scanning a QR code in the monitor menu.

Maximum number of apartments that can be managed from the App: No limit

Maximum number of smartphones/tablets where call divert from the same house can be used: 10 (including administrator's and invited user's devices)

Maximum number of users that can be invited by the administrator: 5

Calls reception: Audio and Video from outdoor panels/concierge units. With pre-view before audio communication is on.

Conversation time: 90 s.

Mute: Yes

Video off: To reduce the data consumption when being in 4G mode

Switching of outdoor panels/cameras: Yes. It allows for switching to other panels/cameras (if any) with the same sequence than the monitors.

Auto-on: Yes. communication possible with 3 outdoor panels/cameras without being called

Activate additional feature (stairlight relay, second door, etc.): Yes. F1 button.

Door opening: Yes, protected by the unblocking code of the smartphone/tablet: PIN, fingerprint, pattern or face ID.

Concierge call: Yes

Calls register: Yes (answered calls in green, missed calls in red)

Settings: Name and picture of the house, Do not disturb, Change password, Ringtone and vibration mode.

Picture &, Video capture: Not from the APP. Only automatically from the monitor

Available languages: 16 (Spanish, English, French, German, Portuguese, Finnish, Czech, Polish, Dutch, Norwegian, Greek, Danish, Swedish, Hebrew, Russian, Arabic)

Peso: 0,2859 kg

Medidas do produto embalado: 17x12,8x4 cm

EAN 13: 8424299094496

